



VHF MARINE TRANSCEIVER IC-M36



"Automatic Volume Adjustment"

"Noise Cancelling Mic"

"Loud, Instant Maximum Audio"

- "Motor handling and unloading"
- "Wharf Crane"
- "Engine noise"
- "Personal watercraft"
- "Forklifts and wharf"
- "Motor boats"
- "Engine noise"
- "Personal watercraft"
- "Roar of waves"
- "Large cargo vessels and tug boats"

CLEAR VOICE BOOST

(Clear Voice + Voice Boost)

In marine environments there are many sources of noise that can affect the quality of your communications, such as engine noise, breaking surf and more. The IC-M36 automatically adjusts the outgoing voice and the incoming audio to compensate for the ambient noise level: whether you're in a loud environment or in a quiet area, the IC-M36 ensures your radio conversation is sent and received as clearly as possible.

And yes, it floats too!

Continuing the legacy of the IC-M34, the IC-M36 floats back up to the surface if dropped overboard, even if the optional speaker microphone, HM-165, is attached.



LOUD button

When you need an instant "boost" in the volume, a simple push of the "LOUD" button gives you full volume immediately. In addition, holding the "LOUD" button mutes the audio output.

Noise cancelling microphone

The sub-microphone on the rear panel inverts phase and cancels out ambient noise from the main microphone. As a result, the IC-M36 reduces the affect of background noise (particularly treble noise) from the transmitted signal and makes it easier to catch voice communication.

Automatic volume adjustment

When in an engine room or high noise environment, the sub-microphone detects the ambient noise and the IC-M36 automatically increases the volume output to suit the surrounding environment.

Low power consumption

Although the IC-M36 delivers a high 6W RF output and 700mW audio output, its current saving circuit offers a practical 8 hours* of operating time with the supplied 980mAh Lithium-Ion battery pack.

* Typical operation with Tx (Hi): Rx: standby=5:5:90

Large buttons and slim dimensions

Thanks to the large, easy-to-operate buttons, the IC-M36 provides intuitive operation. A pinched-waist slender body makes it easy to hold and carry the radio, and is surprisingly compact for a floating radio.

Other features

- Waterproof construction equivalent to IPX7 (1m depth for 30 minutes)
- Dual/Tri-watch functions
- Weather channel with weather alert
- 4-step battery life indicator
- Auto scan function
- Instant access to Ch 16 or Ch 9

SPECIFICATIONS

GENERAL

• Frequency range	:	Tx 156.025–157.425MHz Rx 156.050–163.275MHz
• Usable channel groups	:	INT, USA, CAN, WX channels
• Type of emission	:	16K0G3E (FM)
• Current drain (at 7.4V DC)	:	Tx 6W output 1.5A typical Rx AF max. Internal speaker 300mA typ. External speaker 200mA typ. Power save 10mA typ.
• Operating temp. range	:	–20°C to +60°C; –4°F to +140°F
• Antenna impedance	:	50Ω (STUD)

• Dimensions (W×H×D) (projections not included)	:	62×139.5×43 mm; 2 ⁷ / ₁₆ ×5 ¹ / ₂ ×1 ¹¹ / ₁₆ in
• Weight (approx.)	:	295g; 10.4oz (With BP-252, FA-SC58V, MB-109)

TRANSMITTER

• Output power (Hi/Low)	:	6W/1W 2W/1W (Alkaline cells)
• Max. frequency deviation	:	±5kHz
• Frequency error	:	±10ppm
• Spurious emissions	:	–68dBc typ.
• Adjacent channel power	:	70dB
• Audio harmonic distortion	:	Less than 10% (at 60% dev.)
• Residual modulation	:	40dB

RECEIVER

• Sensitivity (at 12dB SINAD)	:	0.25µV typ.
• Squelch sensitivity	:	0.35µV typ. (at threshold)
• Adjacent Ch. selectivity	:	70dB typ.
• Spurious response	:	70dB typ.
• Intermodulation rejection	:	70dB typ.
• Hum and noise ratio	:	40dB
• Audio output power (at 10% distortion)	:	Internal speaker 700mW typ. (16Ω load) External speaker 350mW typ. (8Ω load)

Supplied accessories:

- Battery case, BP-252
- AC adapter, BC-147SA/BC-174E
- Antenna, FA-SC58V
- Battery charger, BC-173
- Belt clip, MB-109
- Hand strap


Measurements made in accordance with TIA/EIA-603. All stated specifications are subject to change without notice or obligation.

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.




BP-251 BATTERY CASE
Battery case for AAA (LR03)×5 alkaline cells.
Output power: 2W.
BP-252 7.4V/980mAh Li-Ion BATTERY PACK
Provides 8 hours operating time (approx.).
(Typical operation with Tx (Hi): Rx: standby=5:5:90)



BC-173 DESKTOP CHARGER
+ **BC-147SA AC ADAPTER** (for USA)
or **BC-174E AC ADAPTER** (for Asia)
Charges the battery pack, BP-252, in 10 hours (approx.).



BC-162 DESKTOP CHARGER
+ **BC-145A AC ADAPTER**
Rapidly charges the battery pack, BP-252, in 2 hours (approx.).



HM-165 SPEAKER-MICROPHONE
Waterproof construction equivalent to IPX7 (1 m depth for 30 min.).



MB-109 BELT CLIP
Alligator type.
Same as supplied.



FA-SC58V ANTENNA
Soft flexible antenna.
Same as supplied.

Please note : The noise cancellation can produce little or no effect in some conditions depending on type of noise, or the position and distance between the noise source and the microphone, etc. The noise cancellation does not work when an optional external speaker-microphone is connected.

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia and/or other countries. All other trademarks are the properties of their respective holders.

Icom Inc. 1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.

2380 116th Avenue NE,
Bellevue, WA 98004, U.S.A.
Phone: +1 (425) 454-8155
Fax: +1 (425) 454-1509
E-mail: sales@icomamerica.com
URL: <http://www.icomamerica.com>

Icom New Zealand

146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone: +64 (09) 274 4062
Fax: +64 (09) 274 4708
E-mail: inquiries@icom.co.nz
URL: <http://www.icom.co.nz>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay,
Kent, CT6 8LD, U.K.
Phone: +44 (0)1227 741741
Fax: +44 (0)1227 741742
E-mail: info@icomuk.co.uk
URL: <http://www.icomuk.co.uk>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone: +886 (02) 2559 1899
Fax: +886 (02) 2559 1874
E-mail: sales@asia-icom.com
URL: <http://www.asia-icom.com>

Icom Canada

Glenwood Centre #150-6165 Highway 17,
Delta, B.C., V4K 5B8, Canada
Phone: +1 (604) 952-4266
Fax: +1 (604) 952-0090
E-mail: info@icomcanada.com
URL: <http://www.icomcanada.com>

Icom (Europe) GmbH

Communication Equipment
Himmelgeister Str. 100,
D-40225 Düsseldorf, Germany
Phone: +49 (0)211 346047
Fax: +49 (0)211 333639
E-mail: info@icomeurope.com
URL: <http://www.icomeurope.com>

Icom France s.a.s.

Zac de la Plaine,
1 Rue Brindejonc des Moulinais, BP 45804,
31505 Toulouse Cedex 5, France
Phone: +33 (5) 61 36 03 03
Fax: +33 (5) 61 36 03 00
E-mail: icom@icom-france.com
URL: <http://www.icom-france.com>

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,
Clayton, VIC 3168 Australia
Phone: +61 (03) 9549 7500
Fax: +61 (03) 9549 7505
E-mail: sales@icom.net.au
URL: <http://www.icom.net.au>

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"
Bajos A 08174, Sant Cugat del Valles,
Barcelona, Spain
Phone: +34 (93) 590 26 70
Fax: +34 (93) 589 04 46
E-mail: icom@icomspain.com
URL: <http://www.icomspain.com>

Icom Polska

81-850 Sopot, ul. 3 Maja 54, Poland
Phone: +48 (58) 550 7135
Fax: +48 (58) 551 0484
E-mail: icompolkska@icompolkska.com.pl
URL: <http://www.icompolkska.com.pl>